

ConnectCore for i.MX8X Single Board Computer








Table of Content

Page	Name
Page 1	Block Diagram
Page 2	CCIMX8X Power, Control, MCA
Page 3	CCIMX8X Digital interfaces
Page 4	CCIMX8X RF, PCIe
Page 5	Power, bootstrap, reset
Page 6	JTAG, SWD, MicroSD, Mini PCIe, MicroSIM
Page 7	Console, UART, CAN
Page 8	Ethernet1
Page 9	Ethernet2
Page 10	Displays and cameras
Page 11	USB HUB
Page 12	USB Type C, USB mcirAB
Page 13	Audio
Page 14	I2C, XBee
Page 15	Expansion connectors, User LEDs, RF signals
Page 16	GPIO table, System power rails
Page 17	History, Mechanicals











PCIe interface only externally available in non-wireless variants.
R222, R223, R224, R225, R226, R227, C137 and C138 populated
when non-wireless modules is assembled on the SBC PRO.


Power and Reset




Supply Outputs




Supply Inputs



Bootstrap




5V Load switch




miniPCIe

PCIe power supply




PCIe_VCC	R143	R144
4V	68K	12K
3.3V	53.6K	12K


micro SIM




JTAG




SWD



microSD




CAN & RS485




CAN/RS485#	FLEXCAN1	FLEXCAN2	RS485
0	ON	OFF	ON
1	ON	ON	OFF


Console TTL



M4 UART




Gigabit Ethernet




Parameter	Default value	Description
PHYADDRESS[2:0]	001	PHY address set to 0x01
Mode[3:0]	0000	BaseT, RGMII
Int select	0	-

Gigabit Ethernet




Parameter	Default value	Description
PHYADDRESS[2:0]	000	PHY address set to 0x00
Mode[3:0]	0000	BaseT, RGMII
Int select	0	-


LVDS0




MIPI Camera




LVDS1








Parallel Camera




USB_HOST







USB_Type_C




USB_microAB



AUDIO




I2C




I2C3 (3.3V)


Peripheral	7-bit address (Hex)
USB_SS3	0x52
Audio CODEC	0x10
CSI	-
PCle Port	-
Expansion I2C	-

XBee





USER LEDs




System Power Rails

Voltage (V)	Supply Name	Block	Generated by	Current Capability (mA)	Notes
5.0	VIN	Overvoltage Prot	External DC supply	-	
		MCA LDO			
	VIN_PROT	ConnectCore 8X	Overvoltage Prot	-	
		5V load switch			
		USB Host VBUS			
		USB Type C			
		USB microAB			
		PCIe Regulator			
		Expansion connector			
	5V	CAN	Load switch (U7)	-	
LVDS0					
LVDS1					
3.3	3V3_EXT	UART RS-485	PMIC SW7	2500	
		CAN			
		Ethernet1			
		Ethernet2			
		USB Type C PD			
		USB HUB			
		LVDS0			
		LVDS1			
		MIPI CSI			
		Parallel camera			
		Audio			
		XBee			
		Expansion connector			
	PCIe_VCC	PCIe minicard	VIN_PROT	3000	
VCC_MCA	MCA	AP2202	150		
3.0	VCC_LICELL	RTC	External Coin Cell	-	
1.8	1V8_EXT	UART Level shifter	PMIC SW6	2500	
		Audio			
	VCC_SCU_1V8	Bootstrap	PMIC LDO1	400	
	LDO3	MicroSD	PMIC LDO3	400	
1.5	VLDO4_1V5	Mini PCIe socket	PMIC LDO4	400	

GPIO Table

Signal Name	GPIO
AUD_INT#	GPIO3_17
AUD_PWR_EN	GPIO0_14
CAN1_MODE	GPIO1_00
CAN2_MODE	GPIO1_02
CAN/RS485#	GPIO3_23
ENET_PWR	GPIO3_13
EXP_I2C_GPIO	GPIO3_14
EXP_I2C_IRQ_N	GPIO3_15
MIPI_CSI0_RESET_N	GPIO3_21
MIPI_DSI0_IRQ_N	GPIO3_20
MIPI_DSI1_IRQ_N	GPIO3_19
PCIE_DIS_N	GPIO0_30
PCIE_RESET_N	GPIO3_16
PCIE_VCC_EN	GPIO0_31
PCIE_WAKE_N	GPIO0_29
POWER_LED	PTD7
5V_SBC_PWR_ON	GPIO0_13
RGMII1_RESET_N	GPIO3_18
RGMII2_RESET_N	GPIO3_22
RS485_RE#/DE	GPIO3_24
RF_KILL	GPIO0_20
SPI0_IRQ_N	GPIO1_01
USB_HUB_RESET_N	GPIO1_03
USB_PWR	GPIO0_15
USB_SS3_ALERT_N	GPIO4_04
USB_SS3_BUS_SEL	GPIO4_06
USB_SS3_INT_B	GPIO4_03
USB_SS3_SW_PWR	GPIO4_05
USER_LED0	PTD5
USER_LED1	PTD6
VLDO2_VSELECT	GPIO0_19
XBEE_ON/SLEEP_N	PTC4
XBEE_RESET_N	PTC3
XBEE_SLEEP_RQ	PTE20

Power architecture diagram



1	2	3	4	5	6	7	8								
A	Format: DD/MM/YYYY 28/06/2018 - ConnectCore for i.MX8QX Single Board Computer PRO * Initial version: 55002025-01 rev02 17/10/2018 - ConnectCore for i.MX8QX Single Board Computer PRO * 55002025-01 rev03 - PCB board redesign. 21/11/2018 - ConnectCore for i.MX8QX Single Board Computer PRO * 55002025-01 rev04 - Power microSD from 3V3 instead of LDO3. Depopulate R56 and R230 and populate R57 and R231. 27/12/2018 - ConnectCore for i.MX8QX Single Board Computer PRO * 55002025-01 rev05 - Fixed SoM internal P/N - Improved suspend to RAM and power-off power consumption: - R162 changed from 1K to 2.2M - Depopulate R25 and C132 04/02/2019 - ConnectCore for i.MX8QX Single Board Computer PRO * 55002025-01 rev1P - Remove: R56, R230, R246, R249 and R64. - Populate: R57, R162 and R231. 04/04/2019 - ConnectCore for i.MX8QX Single Board Computer PRO * ECO-009688 - 55002025-01 rev2P - No changes on the SBC PRO. Move to the new revision of the SoM (55001984-02 rev2P). 27/05/2019 - ConnectCore for i.MX8QX Single Board Computer PRO * ECO-009766 - 55002025-01 rev3P - No changes on the SBC PRO. Move to the new revision of the SoM (55001984-02 rev3P). 03/07/2019 - ConnectCore for i.MX8QX Single Board Computer PRO * ECO-009955 - 55002025-01 rev4P - Move to the new PCB: 3001575x-04 revA. - Change the voltage shifter (U22) on the IRQ line of the touch controller of the LVDS interfaces so that this line is bi-directional. - Change the strategy around the PWR_ON signal to improve the functionality in low-power modes. - MCA_IO19 has been used on the SoM and is marked as reserved on the SBC. - Add the RC network into the CoinCell charger output. - Add power switches to 3V3 and 1V8 power rails. 25/09/2019 - ConnectCore for i.MX 8X Single Board Computer PRO * ECO-010037 - 55002025-01 rev5P - Move to the new SoM PCB (30015412-04 revA). - No PCB change. 27/09/2019 - ConnectCore for i.MX 8X Single Board Computer PRO * ECO-010139 - 55002025-01 rev6P - U-Boot and MCA firmware update on CC8X SoM. - No PCB change. 27/01/2020 - ConnectCore for i.MX 8X Single Board Computer PRO * ECO-010154 - 55002025-01 rev7P - Label update on CC8X SoM. - No PCB change. 05/03/2020 - ConnectCore for i.MX 8X Single Board Computer PRO * ECO-010425 - 55002025-01 rev8P - Replacing 30015752-04 by 30015752-05 PCB. - Replacing U30 (17050018) by D14 (17000173) - Replacing 50001980-02 SoM P/N by its ship level CC-WMX-JM8E-NN - Replacing FIL1 (21000532) by FIL1 (21000606) 06/10/2020 - ConnectCore for i.MX 8X Single Board Computer PRO * ECO-010845 - 55002025-01 revA - Release to revA without BOM changes.						A								
B							B								
C							C								
D	H1 H2 H3 H4 125mil 125mil 125mil 125mil TXT1 LABEL TEXT 95022431						D								
1	2	3	4	5	6	7	8								
						<table><tr><td colspan="2">Title: History</td></tr><tr><td>Designer: Juan Anzola</td><td>Sheet: 17 of 17</td></tr><tr><td>Variant:55002025-01</td><td>Rev: A</td></tr><tr><td colspan="2">Description: ConnectCore for i.MX8X SBC PRO</td></tr></table>	Title: History		Designer: Juan Anzola	Sheet: 17 of 17	Variant:55002025-01	Rev: A	Description: ConnectCore for i.MX8X SBC PRO		DIGI
Title: History															
Designer: Juan Anzola	Sheet: 17 of 17														
Variant:55002025-01	Rev: A														
Description: ConnectCore for i.MX8X SBC PRO															