



Local User Management

6300-CX, 6310-DX, 6330-MX, and 6350-SR

Local User Management

Skill level: *Beginner*


Goal

To create a new user and/or change the password of the default root user.

Details

Open the configuration profile for the 63xx-series device and make the following changes:

1. To update the root user password, enter in the new password in the in the **Authentication -> Users -> root -> Password** option.
2. To create a new local admin user:
 1. Under **Authentication -> Users -> Add User**, enter in the new username and click **Add**.
 2. Enter in the password for the new user
 3. Under **Groups** for the new user, select the default **admin** group. You can create a new group, or edit the admin group's privileges through the **Authentication -> Groups** section of the configuration profile.
3. Click **Save** or **Update** to apply the changes.

 **NOTE:** After saving a user's password in Accelerated View, it is stored as a salted hash for security purposes. Clicking **show** prior to committing the password will reveal the true value; clicking **show** after that password has been saved reveals the salted hash.

Central management ▾

Modem ▾

Network ▾

VPN ▾

Firewall ▾

Services ▾

Authentication ▾

Idle timeout ▾

Methods ▾

Groups ▾

Users ▾

root ▾

Enable ▾

Password ▾ nondefaultpassword
 Show

Groups ▾

SSH keys ▾

new_user ▾

Enable ▾

Password ▾ new_password
 Show

Groups ▾

| | | |
|----|-------|-------|
| 1. | Group | admin |
|----|-------|-------|

Add Group: Add

SSH keys ▾

Add User: Add

TACACS+ ▾

System ▾

Monitoring ▾