



# Router Mode Setup

## 6310-DX


# Router Mode Setup

Difficulty level: *Easy*

## Goal

---

To setup the 6310-DX as a standard DHCP Cellular Extender with dual WAN failover between the DX's WAN Ethernet port and its cellular modem.

 Once cellular extender mode is enabled, the 6310-DX will use its WAN Ethernet port as the primary Internet connection for all client devices, and the cellular modem will be the backup connection.

## Setup

---

This article assumes the 6310-DX is operating under default settings, which provides passthrough connectivity to a device connected on port 1 of the 6310-DX. For more details on the default settings of the 6310-DX, see the [Default Settings](#) section of the 6310-DX User's Manual. Also, refer to the [Getting started with Accelerated View](#) for details on how to configure a 6310-DX (or the [Local device management](#) section, if you are managing the device without Accelerated View).

## Configuration Steps

---

Open the configuration profile for the 6310-DX and make the following changes.

1. Under **Modem -> Passthrough**, de-select the **Enabled** checkbox.
2. Under **Network -> Interfaces -> LAN**, select the **Enabled** checkbox.